



Cen-Tech Seven Function Digital Multimeter Dial Replacement

This guide will show how to remove and replace the dial.

Written By: Anna Kihm



INTRODUCTION

If the dial is stuck in any particular position it will be necessary to replace. This guide will show how to locate and replace the dial.



TOOLS:

- [Phillips #0 Screwdriver](#) (1)
- [Flathead 3/32" or 2.5 mm Screwdriver](#) (1)



PARTS:

- [Cen-Tech Seven Function Multimeter Dial](#) (1)

Step 1 — Position Device



- Place the meter face down, so the back panel and screws can be seen.

Step 2 — Remove Back Panel Screws



- Unscrew the two 9mm screws on the back panel using a #0 Phillips screwdriver.

Step 3 — Remove Back Panel



- Remove the back panel of the device by lifting upward.
- Remove the battery from the meter before continuing.

Step 4 — Unscrew Motherboard



- Using a 2.5 mm flat screwdriver, remove the four 7mm screws holding the circuit board in place.

Step 5 — Remove Motherboard



- Gently lift the circuit board away from the device casing.
- ⓘ Remove the battery after removing the back cover to reduce the chances of short-circuiting the circuit board.

Step 6 — Locate Dial



- The dial is located in the central part of the device.

Step 7 — Remove Dial



- Carefully remove dial from device by lifting upward.
 - Clean existing dial or replace if necessary.
- ⚠ Take care not to lose the small ball bearings.

To reassemble your device, follow these instructions in reverse order.

This document was last generated on 2017-09-22 07:10:30 AM.